

# SCANPAL EDA51 HC

## Mobile Computer for Healthcare

**Purpose-built with the right combination of features and accessories for light-duty applications in healthcare.**

The healthcare industry faces many challenges. Requirements are evolving rapidly. Mobile computers – purpose-built for healthcare – are critical tools to help address these challenges.

From admissions to inventory management to the point of care, the ScanPal™ EDA51 HC mobile computer is designed for light-duty applications. It features a fast Qualcomm® Snapdragon™ SDM450 processor, robust wireless connectivity, and 12 hours of battery power, so medical professionals can access crucial work apps and information when and where they need it.

Accuracy is essential for delivering quality care. That's why closed-loop medication management and sample collection based on barcode reading is now the standard practice for patient safety. The ScanPal EDA51 HC equips you to instantly and accurately capture this barcode data – even if a barcode is damaged – with its powerful, integrated scanner. You can also document images to aid in patient care with the device's autofocus, 13-megapixel color camera.

And to help support your infection prevention protocols, this mobile device is made with a healthcare-grade housing that you can disinfect frequently over its entire three-year lifespan.

The ScanPal EDA51 HC helps you deliver excellent care at a low total cost of ownership. With its intuitive, modern touchscreen design, the device is easy to use with a short learning curve. In addition, its sleek and pocketable design is comfortable enough to use and carry all day – but rugged enough to survive in demanding healthcare environments. The device is also upgradeable through Android™ Q, giving your organization flexibility and built-in investment protection.



*The ScanPal EDA51 HC is an easy-to-use, sleek, and pocketable assistant that enables caregivers to deliver excellent, patient-focused care. It also lowers the total cost of ownership of a solution that's purpose-built for healthcare.*

## FEATURES AND BENEFITS



Comes with Android O and is technically compatible through Android Q, protecting your investment for the future.



Easy to use and carry, with a 5-inch touchscreen and intuitive smartphone interface in a lightweight, comfortable, and pocketable design.



Get fast, responsive performance and quick access to critical information with the Qualcomm Snapdragon SDM450 octa-core processor.



Easily capture 1D/2D barcode data, even if damaged, with the high-performance N3601 imager, and document everything with the autofocus 13 MP color camera.



Disinfectant-ready housing is specifically designed to withstand frequent exposure to cleaning solutions recommended for the healthcare industry.

**Honeywell**

# SCANPAL EDA51 HC Technical Specifications

## MECHANICAL

**Dimensions:** 157 mm x 78.2 mm x 16.9 mm  
(6.18 in x 3.08 in x 0.67 in)

**Weight:** 272 g (9.59 oz)

**Display Size:** 12.7 cm (5.0 in)

**Resolution:** 1280 x 720 High Definition

**Backlight:** LED

**Touchscreen:** Multi-touch capacitive  
(CTP), GFF

## ENVIRONMENTAL

**Operating Temperature:** -10°C to +50°C  
(+14°F to +122°F)

**Storage Temperature:** -20°C to +70°C  
(-4°F to 158°F)

**Humidity:** 10% to 90% (non-condensing)

**Drop:** Multiple 1.2 m (4 ft) drops to concrete  
at room temperature

**Tumble:** 300 times at 0.5 m (1.64 ft)

**Environmental Sealing:** IP64

## SYSTEM ARCHITECTURE

**Processor:** Qualcomm Snapdragon SDM450,  
1.8 GHz octa-core

**Memory:** 2 GB RAM/32 GB Flash

**Operating System:** Android 8.1

**Storage Expansion:** MicroSDHC  
(up to 128 GB)

**Camera:** 13-megapixel color camera

**PC Interface:** Micro USB 2.0

**Battery:** Li-Ion, 3.8 V, 4,000 mAh, removable

**Real-Time Clock (RTC):** 10 minute backup  
via super-cap

**Charging Time:** 4.5 hours

**Battery Runtime:** 12 hours

**Scan Engine:** Honeywell N3601 Slim Imager  
Engine (1D/2D barcode symbologies)

## LED

**Battery Status Indicator:** red/green/blue

## SENSORS

Acceleration sensor, light sensor, and  
proximity sensor

## LOCALIZATION & LANGUAGE

Worldwide English

## WIRELESS CONNECTIVITY

**WLAN:** IEEE 802.11 a/b/g/n/ac

**WLAN Security:** WEP, 802.1x, TKIP, AES,  
LEAP, PEAPv0, PEAPv1, EAP-M, SCHAPv2,  
EAP-GTC, EAP-TLS, EAP-TTLS, WPA-PSK,  
WPA2

**Bluetooth®:** Bluetooth Class 4.2

**NFC:** Integrated Near Field Communication

## ACCESSORIES (STANDARD)

**USB Communication Cable:** Micro USB 2.0  
(communicates to PC, supports adapter/USB  
charging)

**USB Wall Adapter:** 5 V/2 A

## ACCESSORIES (OPTIONAL)

### Hand Strap

### Scan Handle

**Home Base:** Charges one terminal and one  
replaceable battery simultaneously

**Four-Bay Battery Charger:** Charges four  
batteries simultaneously

**Four-Bay Terminal Charger:** Charges four  
terminals simultaneously

Backward-compatible with ScanPal EDA50  
accessories.

## WARRANTY

One-year factory warranty

For a complete listing of all compliance approvals  
and certifications, please visit  
[www.honeywellaidc.com/compliance](http://www.honeywellaidc.com/compliance).

For a complete listing of all supported barcode symbologies,  
please visit [www.honeywellaidc.com/symbologies](http://www.honeywellaidc.com/symbologies).


ScanPal is a trademark or registered trademark of Honeywell  
International Inc.

Android is a trademark or registered trademark of Google LLC.

Qualcomm and Snapdragon are trademarks or registered  
trademarks of Qualcomm Incorporated.

Bluetooth is a trademark or registered trademark of Bluetooth  
SG, Inc.

All other trademarks are the property of their respective owners.



## For more information

[www.honeywellaidc.com](http://www.honeywellaidc.com)

[www.android.com/AER](http://www.android.com/AER)

## Honeywell Safety and Productivity Solutions

9680 Old Baires Road

Fort Mill, SC 29707

800-582-4263

[www.honeywell.com](http://www.honeywell.com)

ScanPal EDA51 HC Data Sheet | Rev B | 01/20  
© 2020 Honeywell International Inc.

THE  
FUTURE  
IS  
WHAT  
WE  
MAKE IT

**Honeywell**